



PRODUCT SPECIFICATION
Wireless doorbell
Doorbell USB
BXD106

Features:	Wireless doorbell with possibility of own tunes/melodies.
Maximum no. of Bell pushes:	Unlimited.
Frequency:	868 MHz. (New frequency which ensures minimum interference from other wireless units). A personal code is set by use of 6 buttons to prevent interference of the signal by other units within distance (64 possible combinations). IMPORTANT: the code for chime and every Bell push must be identical.
Transmission range:	200 metres in free sight between each Bell push and the chime.
Tunes:	5 selectable tunes (clear polyphonic tones) with maximum playing time of 8 seconds. Three of them can be changed to own tunes/melodies in MIDI format by connection to computer with enclosed USB cable and software (compatible with Windows XP, 2000, ME, and 98 (USB driver also necessary with Windows 98)).
Volume:	High, low or off.
Diode:	The diode on the Bell push illuminates as confirmation of transmission of signal. Flashes on the chime when someone is ringing the bell. Can be switched on/off on the chime. Always flashing when battery is low.
Mounting:	Chime: Free standing or mounted on wall. Bell push: On wall or door frame.
Power supply:	Chime: 3 pcs. AA batteries. Bell push: 2 pcs. AAA batteries (included). Possibility of electric power connection to chime (adaptor – not included).
Dimensions – chime:	175 x 122 x 60 mm.
Dimensions – Bell push:	106 x 36 x 28 mm.