

PRODUCT SPECIFICATIONS - Radio controlled clock



BXM112 - Radio controlled clock

Features:	The exact date and 24hours time. Built-in light and snooze. Automatic summer and winter time.
Data field:	Within a radius of 1500 km from Frankfurt (except for GB).
Operation:	
ALARM	For setting the alarm when held down for more than 2 seconds. The actual segment to be set is flashing. When pressing shortly the set alarm time is displayed.
ALARM ON/OFF	Activates/ deactivates the alarm.
LIGHT/SNOOZE	Activates the built-in light for app. 5 seconds or activates the snooze function for intervals of 8 minutes.
TIME A	For setting the time manually or setting the alarm.
Operation in battery compartment:	
KEY LOCK	Keylock (eg. when travelling).
MANUAL SET	For manual setting of time. Then press TIME A and confirm the set time by pressing MANUAL SET again.
ALARM	Choose between 2 types of alarm: Crescendo (rises in frequency and volume) or one-level alarm.
Batteries:	2 pcs. "AAA" batteries.
Update after change of batteries:	Immediately and constantly for 10 minutes. Then at the clocks hours 0:00, 1:00, 2:00, 3:00, 6:00, 12:00, 18:00.
Dimensions:	140 x 62 x 22 mm.
Weight:	130g.
Error:	
	- Change the batteries.
	- Remove the clock to another place, where a clear signal can be obtained (Eg. by turning it 90 degrees).